

# MiFi 8000 Mobile Hotspot Reference Guide

## About Your MiFi 8000

1. **Power Button:** Powers the MiFi 8000 on and off.
2. **Color Touchscreen (2.4 in):** Displays device status, data usage, and number of users connected. Swipe left/right/up or down to access available menu options.
3. **Test Port**
4. **USB-C Port:** Use to connect the QuickCharge charger, Internet over USB-C, to charge one additional wireless device, and MiFi Share file sharing via mass storage.
5. **Test Port**
6. **Master Reset Hole:** Use to reset MiFi 8000 back to original factory settings.
7. **Battery Compartment:** The battery is pre-installed.
8. **Battery Removal Divot:** Insert a fingernail here and lift to remove the battery.
9. **IMEI (Serial Number)**




# Using Your MiFi 8000's Touchscreen






## The Home Screen

The Home screen lets you see what your MiFi 8000 is doing at a glance.

1. Signal Strength
2. Data Usage
3. Wi-Fi On/Off
4. Menu
5. Wi-Fi Name/Password
6. Number of Wi-Fi devices connected to your MiFi 8000




MiFi 8000 Home Screen


At the top of the screen, you'll see status indicators for network signal strength , data traffic activity , unread Inseego system messages , roaming , and battery .

The middle of the screen shows you if Wi-Fi is on or off, and how many devices are connected to your MiFi 8000's Wi-Fi network.


Your Wi-Fi Name and Password are next. For information on changing your Wi-Fi Name and Password, see (See Managing MiFi 8000 Settings.).



Tap Menu to Open Menu Options



Swipe Up/Down to Desired Option



Tap to View Desired Option

# Managing Wi-Fi

The Wi-Fi page lets you manage your MiFi 8000's Wi-Fi settings. This page is divided into 3 tabs:

**SETTINGS** • **PRIMARY NETWORK** • **GUEST NETWORK**

## Settings

From the Settings tab, you can turn your MiFi 8000's Wi-Fi ON/OFF, change Network and Wi-Fi ON/OFF, change Network and Wi-Fi Connections Settings, and customize Band Settings.

- To turn **Wi-Fi ON/OFF**, use the switch and then click **Save Changes** at the bottom of the screen.
- To select or turn off **Band Selections for the Primary and Guest networks**, mark the buttons for 2.4 GHz Band and 5 GHz Band. Choose **Off**, **Primary network**, or **Guest network**.
- To change the maximum number of **Wi-Fi devices** that can connect to the MiFi 8000 (the default is set to 15), make your selection from the **Limit connected devices** to dropdown menu.
- To customize the **Band Settings**:
  1. Click on the **2.4 GHz Band Settings** or **5 GHz Band Settings** link to display the available Band Settings options.
  2. Make your **Mode**, **Channel**, and **Bandwidth** selections from the dropdown menus and then click **Save Changes**.

The screenshot shows the 'Wi-Fi' settings page for a MiFi 8000 device, with the 'Settings' tab selected. The page has three tabs: 'Settings', 'Primary Network', and 'Guest Network'. Below the tabs, a note states: 'These settings apply regardless of which network (Primary, Guest, or both) is in use. Changes made to these Wi-Fi settings will be applied to all networks.' The 'Wi-Fi' section contains a toggle for 'Allow Wi-Fi devices to connect to this MiFi' (turned on), a toggle for 'Allow Wi-Fi setting changes from the MiFi's touchscreen display' (turned on), and a dropdown menu for 'Limit number of connected devices to' set to '15'. The 'Band Selection' section has two columns for '2.4 GHz Band' and '5 GHz Band'. Under '2.4 GHz Band', 'Primary network' is selected with a blue dot, while 'Guest network' and 'Off' are unselected. Under '5 GHz Band', 'Primary network' is selected with a blue dot, while 'Guest network' and 'Off' are unselected. Below this are two sections: '2.4GHz Band Settings' and '5GHz Band Settings'. The '2.4GHz Band Settings' section shows '802.11 Mode' as '802.11bgn' and 'Channel' as 'Automatic'. The '5GHz Band Settings' section shows '802.11 Mode' as '802.11acn', 'Bandwidth' as '80 MHz', and 'Channel' as 'Automatic'. A blue 'Save Changes' button is at the bottom.

# Managing Wi-Fi (continued)

## Primary Network

From the Primary Network tab, you can change your Wi-Fi Name (SSID) and Password (Key), select the type of security, and turn Options ON/OFF for your primary network.

- To change the Primary Network Wi-Fi Password (SSID) enter the new Wi-Fi name into the field.
- To change the type of Wi-Fi security for the Primary Network, choose an option from the Security dropdown menu.
- To change the Primary Network Wi-Fi Password (Key), enter the new password into the field or click **Generate New Key**. Then click **Save Changes**.
- To turn Options, such as Broadcast Wi-Fi Name (SSID) and WPS, ON/OFF for the Primary Network:
  1. Click the **Options** link to display available options. Options currently turned ON will display with a checkmark in a red box.
  2. Click the checkboxes to turn options ON or OFF and then click **Save Changes**.

The screenshot shows the 'Wi-Fi' settings page with three tabs: 'Settings', 'Primary Network', and 'Guest Network'. The 'Primary Network' tab is selected. A note states: 'NOTE: For added security, share your guest network instead of your primary network.' The 'Settings' section includes a text input for 'Primary network name (SSID)' containing 'MIFI8000', a dropdown for 'Security' set to 'WPA2 Personal PSK (AES)', and a 'Password' input field with a 'Generate new password' button. The 'Options' section has four checkboxes: 'Hide primary network name (SSID) on the touchscreen display' (unchecked), 'Hide password on the touchscreen display' (unchecked), 'Broadcast primary network name (SSID)' (checked), and 'Wi-Fi privacy separation' (unchecked). A 'WPS' checkbox is also checked. A blue 'Save Changes' button is at the bottom.

## Guest Network

The same settings described above for the Primary Network are available for the Guest Network.


# USB File Share

USB File Share lets you share files and folders with connected devices on the MiFi 8000's Wi-Fi network when a USB mass storage device is connected to the USB C port.

To set-up your MiFi settings:

1. From the Home screen, tap **Menu > USB File Share**.
2. Select your desired option and tap the **ON/OFF** button to turn the setting ON or OFF.

**NOTE:** To see instructions on how to access shared folders, sign in to the MiFi 8000 Admin Website and go to **USB File Share > How do I access the shared folders?**



# Help

You can get help right from your MiFi 8000's touchscreen.

1. On the Home screen, tap **Help** to open the Help screen options. Help options include **Admin Website**, **Guest Wi-Fi**, **Wi-Fi Protected Setup (WPS)**, **Tutorial**, **Unlock SIM**, **Universal Charging**, **MiFi Share** and **GPS**.
2. Swipe up/down to highlight the desired Help option, then press to display option choices and information.
3. Tap **<** to return to the Menu screen, or the Home icon to return to the Home screen.

